

MMX-44UFX - Mixer



8-channel audio mixer, with 12 input, DSP effect unit and USB interface. Plug and mix!

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full duplex USB port (allows for simultaneous recording and reproduction) for the reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels, each with gain control, 3-way equalizer, low cut and pan pot
- 4 stereo input channels, each with balance control
- DSP with 100 different effects
- Aux send output
- Control room function
- Tape record/play connections
- +48 V phantom power, can be switched centrally
- Adjustable headphone output
- Stereo LED level display
- Power supply via supplied PSU

Technical data:

Mic, mono	: 0.5 mV, bal.
Line, mono	: 1 mV
Line, stereo	: 10 mV, bal.
Insert, mono	: -
Tape, stereo	: 100 mV
Aux, stereo	: -
Master, stereo L/R	: 650 mV
Control room, stereo	: 2 V
Record, stereo	: 650 mV
Insert, mono	: -
Aux1, mono	: 9.5 V
Aux2, mono	: -
Headphones, stereo	: ≥ 8 Ohm
Frequency range	: 20-20,000 Hz
THD	: < 0.05 %
S/N ratio	: > 74 dB
Crosstalk	: -63 dB
Bass	: ± 15 dB/80 Hz
Midrange	: ± 15 dB/2.5 kHz
Treble	: ± 15 dB/12 kHz
Phantom power	: +48 V
Power supply	: via suppl.PSU
Admiss. ambient temp.	: 0-40 °C
Dimensions	: 280x65x260 mm
Weight	: 2.5 kg